


1977-78

B.E.R.N.I. (VEROBOARD VERSION)

COPPER-SIDE (ENLARGED)

(2.7 x 1.35")
9 x 18 HOLES.

To Sw₁



Finished 3/1979


20th Son

1979

Very

california

BROWN BLANK BOARD




CIRCUIT DIAGRAM.

R-5 1976 (ASTABLE MULTIVIBRATOR / BISTABLE FLIP-FLOP!)


FROM 20 JUN 79

CONNECTIONS.



BEND WIRES AS SHOWN

ZN2926 (G).



BC107. BC108

UNDERSIDE VIEWS.

WHITE BAND



COMPONENTS.

VEROBOARD - 0.15" MATRIX.

- R₁ --- 2.2 KΩ. (RED, RED, BROWN).
- R₂ --- 220 Ω. (RED, RED, BROWN).
- R₃, R₆ --- 10 KΩ. (BROWN, BLACK, ORANGE).
- R₄, R₅ --- 15 KΩ. (BROWN, GREEN, ORANGE).
- * R₈ --- 100 Ω. (BROWN, BLACK, BROWN).
- C₁, C₂ --- 0.01 μF (10,000 P.F.) (MAY BE CODED BROWN, BLACK, ORANGE)
- LED₁, LED₂ --- TIL 209 (OR ANY!)
- * DZ₁ --- 6.2 V, 400 mW, ZENER. (BZY89C5V2).
- TR₁, TR₂ --- ZN2926 (GREEN) or BC107/8.
- SW₁ --- PUSH BUTTON (PUSH TO MAKE).
- SW₂ --- ON/OFF (S.P.S.T.)

* NOTE. IF A 6V SUPPLY IS USED, OMIT DZ₁, AND REPLACE R₃ BY A WIRE LINK.